




32Ch Wet-Sponge R-Net for LiveAmp

Electrode Layout and Channel Assignment



Details for Users

Ordering Information

For ordering please give **Article Number** and **Size** (e.g. RNP-LA-32, 57):

- Article Number: **RNP-LA-32**
- Size (given in cm head circumference):
 - 61 Adult XL
 - 59 Adult L
 - 57 Adult M
 - 55 Adult S
 - 53 Child/Adolescent L
 - 51 Child/Adolescent M
 - 49 Child/Adolescent S
 - 47 Infant XXL
 - 45 Infant XL
 - 43 Infant L
 - 41 Infant M
 - 39 Infant S
 - 37 Neonate L
 - 35 Neonate M
 - 33 Neonate S

The catalogue-number comprises the cap as described, serial number, this document; a memory-stick with manual and bvef-file, and the saltwater net accessory kit SNAK, consisting of 35 spare sponges and 5 pedestals, all packed in a labelled cardboard box. For further information about accessories or consumables, please visit our website or contact our local distributor.

Please adhere to Manual

The manual explains in detail how to prepare, mount, and adjust the cap. Maintenance, cleaning, and disinfection are covered, and what to do when repair is needed. There are several features to improve fit. Please adhere to manual.

Electrodes

The electrodes have Ag/AgCl sensors. They are number-labelled at the sensor end. The cables leave the cap plait-like occipitally, pointing downwards. The length of cable trees is approx. 120 cm. The connector plugs directly into LiveAmp.

Theta/Phi-Coordinates

Please find a table with Theta/Phi-Coordinates of all electrode sites at the end of this file.

Table of Coordinates for RNP-LA-32

| Ch-No. | Name | Theta | Phi |
|--------|------|-------|-----|
| 1 | Fp1 | -90 | -72 |
| 2 | Fz | 45 | 90 |
| 3 | F3 | -60 | -51 |
| 4 | F7 | -90 | -36 |
| 5 | F9 | -113 | -36 |
| 6 | FC5 | -69 | -21 |
| 7 | FC1 | -31 | -46 |
| 8 | C3 | -45 | 0 |
| 9 | T7 | -90 | 0 |
| 10 | CP5 | -69 | 21 |
| 11 | CP1 | -31 | 46 |
| 12 | Pz | 45 | -90 |
| 13 | P3 | -60 | 51 |
| 14 | P7 | -90 | 36 |
| 15 | P9 | -113 | 36 |
| 16 | O1 | -90 | 72 |
| 17 | Oz | 90 | -90 |
| 18 | O2 | 90 | -72 |
| 19 | P10 | 113 | -36 |
| 20 | P8 | 90 | -36 |
| 21 | P4 | 60 | -51 |
| 22 | CP2 | 31 | -46 |
| 23 | CP6 | 69 | -21 |
| 24 | T8 | 90 | 0 |
| 25 | C4 | 45 | 0 |
| 26 | Cz | 0 | 0 |
| 27 | FC2 | 31 | 46 |
| 28 | FC6 | 69 | 21 |
| 29 | F10 | 113 | 36 |
| 30 | F8 | 90 | 36 |
| 31 | F4 | 60 | 51 |
| 32 | Fp2 | 90 | 72 |
| Ref | FCz | 23 | 90 |
| Gnd | Fpz | 90 | 90 |

These values are standardized to a Theta of 90° for the plane through Fpz, T7, T8, Oz.

The signs follow this convention:

